



SEPTEMBER 2021



Update on cable compatibility for Broadcast Headsets:

HMD 300 PROseries, HMD/ HME 26-II series, HMD/HMDC/ HME 27series






MODULAR CABLING SYSTEM

The HMD 300 PRO series, HMD/HME 26-II and HMD/HME/HMDC 27series utilizes the modular cabling system from the cable-II-series. The headset cables can accommodate multipin connectors or independent connectors for mic and headphone. Cable options include straight cables with a coiled segment that eliminates structure born noise, and a fully coiled cable.



MODULAR HEADSET CABLES

MODEL	ARTICLE	DESCRIPTION	COMPATIBILITY	IMAGE
CABLE-II-X3K1-GOLD	508546	Straight copper cable with coiled segment to eliminate structure born noise. Reinforced with Aramid for improved durability, and softer shield for greater flexibility. XLR-3 connector and 6,3 mm (1/4") jack plug with gold plated contacts, 2 m	<ul style="list-style-type: none">• HMD 300 PRO• HMD 301 PRO• HMD 300-XQ-2• HMD 26-II• HME 26-II-P48 *→ (not HME 26-II)• HMD 27/ HMDC 27• HME 27 *	
* P48 power supply needed because P48 amp is integrated in the earcup of the headset				
CABLE-II-X3K1-P48	505783	Straight copper cable reinforced with Aramid for improved durability with short coiled part for minimum structure born noise with XLR-3 connector and 6,3 mm (1/4") jack with P48 amp, 2 m	<ul style="list-style-type: none">• HME 26-II **→ (Not HME 26-II-P48 *)→ (Not HME 27 *)	
* because P48 amp is integrated in the earcup of the headset				
** P48 power supply is needed				
CABLE-II-X4F	505784	Straight copper cable with coiled segment to eliminate structure born noise. Reinforced with Aramid for improved durability. XLR-4F connector, 2 m	<ul style="list-style-type: none">• HMD 300 PRO• HMD 301 PRO• HMD 26-II• HME 26-II→ (Not HME 26-II-P48 *)• HMD 27→ (Not HME 27*, not HMDC 27*)	
* because P48 amp is integrated in the ear cap				



MODEL	ARTICLE	DESCRIPTION	COMPATIBILITY	IMAGE
CABLE-II-X5	505785	Straight copper cable with coiled segment to eliminate structure born noise. Reinforced with Aramid for improved durability. XLR-5M connector, 2 m	<ul style="list-style-type: none"> • HMD 300 PRO • HMD 301 PRO • HMD 26-II • HME 26-II → (Not HME 26-II-P48 *) • HMD 27 → (Not HME 27*, not HMDC 27*) 	
			* because P48 amp is integrated in the ear cap	
CABLE-II-6	508545	Straight copper cable with coiled segment to eliminate structure born noise. Underminated end, 1.85 m	<ul style="list-style-type: none"> • HMD 300 PRO • HMD 301 PRO • HMD 26-II • HME 26-II • HME 26-II-P48 * • HMD 27/ HMDC 27 * • HME 27 * 	
			* P48 Power supply necessary	
CABLE-II-8	505797	Straight copper cable with coiled segment to eliminate structure born noise. Reinforced with Aramid for improved durability. Underminated ends, 2 m	<ul style="list-style-type: none"> • HMD 300 PRO • HMD 301 PRO • HMD 26-II • HME 26-II • HME 26-II-P48 * • HMD 27/ HMDC 27 * • HME 27 * 	
			* P48 Power supply necessary	
CABLE-H-X3K1	502456	Coiled copper cable with XLR-3 connector and 6,3mm (1/4") jack, 3 m	<ul style="list-style-type: none"> • HMD 26-II • HME 26-II-P48 * → (Not HME 26-II) • HME 27 * 	
			* P48 power supply needed	
CABLE-H-X4F	502457	Coiled copper cable with XLR-4F connector, 3 m	<ul style="list-style-type: none"> • HMD 26-II • HME 26-II → (Not HME 26-II-P48 *) 	
			* because P48 amp is integrated in the ear cap	



MODEL	ARTICLE	DESCRIPTION	COMPATIBILITY	IMAGE
CABLE-H-X5	502458	Coiled copper cable with XLR-5M connector, 3 m	<ul style="list-style-type: none">• HMD 26-II• HME 26-II → (Not HME 26-II-P48 *)	
* because P48 amp is integrated in the ear cap				
CABLE-H-6	502533	Coiled copper cable. Unterminated end, 3 m	<ul style="list-style-type: none">• HMD 25-II• HME 26-II• HME 26-II-P48 *• HME 27 *	
* P48 Power supply necessary				